Western Electric Co., Incorporated, Engineering Dept., New York. (2 Pages) Page #1. Issue 1 - BT-502272. November 4, 1921.

METHOD OF OPERATION TRUNK CIRCUIT

Ring-Down Intercepting - Arranged For Routine Instructions On Defective Final Multiple Bank Terminals - Special "A" Switchboard - Power Driven Machine Switching System.

GENERAL DESCRIPTION

- 1. This circuit is used with subscriber's lines whose final multiples are defective and with intercepting operator's cord circuits whose sleeves are connected to battery through a maximum resistance of 220 ohms.
- 2. When the final multiple of a line is defective the tip and ring of this trunk are connected to the tip and ring of the defective final multiple. When a call terminates on a defective final multiple ringing current from the incoming selector lights a lamp at the intercepting operator's position. When the plug of a cord is inserted in the trunk jack, the lamp is extinguished and the ringing current is tripped. The calling subscriber is then instructed how to proceed in order to communicate with the called party.

DETAILED DESCRIPTION

- 3. When this trunk circuit is selected by the final selector and ringing current from the incoming circuit is applied to the tip and ring of this circuit, the RD relay operates through its inner winding and locks through its outer winding under the control of the SL relay, lighting the trunk lamp at the intercepting operator's position. When the plug of an intercepting operator's cord is inserted in the trunk jack the SL relay operates, opening both the inner and outer windings of the RD relay which releases. The RD relay released, extinguishes the lamp.
- 4. When the plug of the cord is withdrawn from the jack the SL relay releases restoring the circuit to normal.

Section States & ATTO AS SECTIONS ENDERTH BUSINESS The state of the s Topography out them to the topography the topography of the topogr same and provide the same to some and a security of the same and a security of the control of the co The state of the s THE ROSE BY CONCOLDED AT ANY CONTRACT OF STREET, AND ANY C A CONTRACT OF THE SET The state of the s Man of the first of the first state of the first st Andrew Strategicker (1980) Andrew Strategick (Velice the second of the secon Therefore the second of the se The state of the s earth are at taking the same personal property of

CIRCUIT REQUIREMENTS

THE REALIUST REQUIREMENTS SHOWN BELOW ARE FOR MAINTENANCE USE ONLY.

	CERATE	NON-OPERATE	RELEASE
Ell (SL)	Redj014 amp. To:t .021 amp. W.J.C028 amp.	Readj010 amp. Test .0095 amp.	
E608 (SL)	Readj065 amp. Test .073 amp. W.C.C080 amp.	Readj044 amp. Test .041 amp.	
G18 (RD) Inner winding	Special requirements to 1 Readj018 amp. Test .019 amp. W.C.C. A.C. amp.	nsure A.C. operation.	Readj010 amp. Test .0095 amp.
Outer winding	Test .020 amp. W.C.C045 amp.		

Company of the part of the par

ENG. — CHMcC-JO. 11/10/21

= + 1 , 4 .

CHK'D.--ACTH-CWP.

The State of the second

A STATE OF S

Service of the state of the

The following solution of the second solutions and the second solutions of the

APPROVED - C. L. SLUYTER, G.M. L.

· Proping Residualist

· 21

art Olda - Gradi 4 m 32 m 4 mm a to the setting of the

w Egite with We the first of the first

-

, A the contract of the said

The second of th

> SERVICE SERVICES **■**₹400 34% + 310 4

and there is the transfer of the